



## NEVABOOST 140 230V 12V



### Overview

#### NEVABOOST 140 230V 12V

cod. 807541

Battery charger for charging free electrolyte batteries (WET) with 12 V voltage.

Protected against overloads and polarity reversal.

Equipped with selector for normal, quick charge/help with starting (BOOST&GO) Equipped with ammeter.



1 PH 230V



VAN



EAC CERTIFICATION



CAR



CE MARKING

### Technical data

CODE	CODE 807541	RATED CHARGE CURR. EN60335-2-29	DIMENSIONS 17 - 25 - 16,5 cm
SINGLE PHASE MAINS VOLTAGE 230 V		START CURRENT 1V/C EN60335-2-29	WEIGHT 5,2 kg
MAINS FREQUENCY 50 - 60 Hz		MIN. RATED REFERENCE CAPACITY 10 Ah	EAN CODE 800489764143 0
CHARGING ABSORBED POWER 230 W		MAX RATED REFERENCE CAPACITY 200 Ah	PIECES/PALLET 95 pz/pallet
CHARGING VOLTAGE 12 V		ADJUSTMENT POSITIONS 2	PIECES/PALLET - B 76 pz/pallet - B
EFFECTIVE CHARGING CURRENT 20 A			



## NEVABOOST 140 230V 12V

---

### Included Accessories

CABLE 4 MMQ 1,5 M AND WORK CLAMP - 123987

CABLE 4MMQ 1,5M + POSITIVE CLAMP - 123988